

- Voltage Supply 480-600-690V
- Internal Fuse on product range from 30 to 800A
- 100 kA Short Circuit Current (SCCR) up to 600V
- SSR and Analog Input
- Zero Crossing & Burst Firing
- HB alarm to diagnostic Partial Load Failure
- Comply with EMC, cULus® 508 listed and cUL® listed

CD AUTOMATION

POWERED BY INNOVATION

REVO S

THE THYRISTOR EVOLUTION






We are delivering Real Cost Benefits



www.cdautomation.com
 Revo S Catalog 2021

WHY CHOOSE REVO?

WE DESIGNED A SUPERIOR PRODUCT



With the market place becoming more competitive we had a choice to make. Design a product a little cheaper but possibly not as good, or design a new innovative product where its added value is clear for all to see. We chose the latter, in line with our long-term philosophy.

NO COMPROMISE

Heatsink and thyristor junctions generously sized to guarantee a long life for the thyristor unit (see figure 2)

- Units working at low junction thyristor temperature with 20% margin on max temperature
- Strong connection design between the block terminal and thyristor semiconductor connection allows for generous sizing
- All the copper connections treated against oxidation
- Rugged construction for electronic and plastic parts
- Protection against over voltage

HAVE A CLOSER LOOK

Open a CD Automation thyristor unit and any of our competitors, you will discover the difference and see why we can offer a longer life warranty (see below tab).

ESTIMATED POWER CYCLES OF AL WIRE BONDED DIES

	dT	Tj max \°C 100°C	110°C	120°C	130°C	140°C
Tj start \°C	80°C	248.000				
	70°C	320.200	110.000			
	60°C	464.000	145.500	51.100		
	50°C	782.000	216.000	69.100	24.800	
	40°C	1.600.000	372.000	105.000	34.100	12.500
SSR	30°C	4.800.000	793.000	184.000	52.500	17.500
Single Cycle	20°C	25.400.000	2.400.000	400.000	94.000	27.500
			12.800.000	1.200.000	209.000	50.000
				6.700.000	645.000	112.000
					3.600.000	353.000
						2.000.000

CD Automation

CD predicted life working in Single Cycle.

CD Automation

CD predicted life with SSR Input and ZC Firing.

COMPETITORS

Predicted life of majority of competitors working at 130°C with SSR Input and ZC firing.

SAVE SPACE = SAVE MONEY

AN INNOVATIVE ENGINEERING SOLUTION THAT WILL DRAMATICALLY SAVE WIRING & LABOR

With a reduction of 50% space, it's easy to save hundreds off the cabinet price.

LEFT SIDE (TRADITIONAL)

Mounted on the baseplate are a Fuse & Fuseholder, 40A Solid State Relay and a Current Transformer.

RIGHT SIDE (INNOVATIVE)

Mounted on the same baseplate are two Relay 40A units, each having the same components as the traditional unit. This simple example demonstrates a 50% saving of panel space.

THE NEW REVO S FAMILY

Can be put together with little technical knowledge

- SSR Solid State Relay with Zero Crossing
- SSR Solid State Relay + Fuse & Fuse Holder
- SSR Solid State Relay + Fuse & Fuse Holder + Current Transformer and Heater Break Alarm
- Different versions with or without heat sink
- Single and three phase thyristor units

OPTIONS

- Heater Break Alarm for partial or total load failure
- Analog Input and Burst Firing
- Connecting with REVO PC will remove power peaks and add communications
- Thyristor short circuit failure



Traditional

Innovative

KEY BENEFITS INCLUDE:

- Space reduction of 50%, labour reduction of 1 hour per control zone, high reliability
- If one zone fails a non-technical user can substitute it with spare units in few seconds

WHAT REVO OFFERS?

- Modularity of its components
- Configurability that allows increased product performance
- REVO's 'value-add' capable of saving 50% of labour and space
- Innovation based on knowledge of process
- International assistance from around the world via trained distributors and joint venture multi-national companies
- Dynamic organization with total customer flexibility at the core of its philosophy

REVO IS A SYSTEM NOT A SIMPLE PRODUCT



- Includes all key components of a typical temperature control zone
- Wiring & mounting accessories included
- Designed as a total block of automation



GLOSSARY

ZERO CROSSING ZC

ZC firing mode is used with the logic output from a temperature controller and so the thyristor operates like a contactor. The cycle time is performed by the temperature controller. Zero Crossing minimizes interferences as the thyristor unit switches ON-OFF at zero voltage.




BURST FIRING BF

This firing is performed within the thyristor unit at zero volts, producing no EMC interference. Analogue input is necessary for BF and the number of complete cycles can be 4-8-16 Cycles for 50% power demand.


HEATER BREAK (H.B.)

Optional electronic circuit capable of detecting all types of heating zone faults. Each zone, via the units front panel, can be calibrated by the user to set the alarm value for partial or total load failure. The capability to identify a partial load failure is 1/5 or 20%. The H.B. Alarm is microprocessor based and can automatically set its alarm value when a digital input is activated or when the CAL push button is selected on the front panel.



Heater Break Alarm load failure

To ensure that the automatic set value is not taken from an unstable current value, the circuit will read the current 5 times and store the average value. When there are 3 equal average values in sequence, it will take this value and multiply by 0.8 to compensate for any voltage fluctuations. The intelligent circuit can also detect if the SCR (switching device) has become open circuit.



Heater Break Alarm short circuit on scr

WHAT DO OUR CUSTOMERS WANT?

THEY WANT A POSITIVE EXPERIENCE WITH OUR TOTAL SOLUTION, NOT JUST A CHEAP PRICE!

KNOWLEDGEABLE SALES TEAM

We have a team of sales engineers focused on core business products only. An expert at no cost, not an engineer with a big catalogue and little product knowledge, will welcome customers. Easy access to engineers when you need a special performance project.

EASY TO DO BUSINESS WITH US

Fast reaction to your enquiry, short lead times, timely production of order acknowledgement, invoices etc. Catalogues & manuals of all our products plus configuration software, available free of charge from our web-site. Our people are always welcoming to our customers.

FAST SERVICE

Excellent pre sales and after sales service including engineering support.

DIGITAL DOCUMENTATION ON CDAUTOMATION.COM

- Bulletins
- Manuals
- Applications
- Help desk



REVO S & SSR FEATURES AND DIMENSIONS

DESCRIPTION		REVO SSR	REVO S 1PH		REVO S 2PH		REVO S 3PH	
CODE		SSR	RS1		RS2		RS3	
MAIN VOLT.	Max voltage 480V	●	●		●		●	
	Max voltage 600V	●	●		●		●	
	Max voltage 690V		● ≥60A		● ≥60A		● ≥60A	
LOAD TYPE	Single phase	●	●					
	3 phase load star no neutral or delta				●		●	
	3 phase load star with neutral						●	
	3 phase load open delta						●	
INPUT	SSR 4:30VDC	●	●		●		●	
	4:20 mA	○	○		○		○	
	0:10 Vdc	○	○		○		○	
	Digital Potentiometer	○	○		○		○	
FIRING	Zero crossing	●	●		●		●	
	Burst firing 4-8-16	○ (1)	○ (1)		○ (1)		○ (1)	
OPTION	Heater break + thyristor short circuit	○	○		○		○	
	Integrated fixed fuses		● >40A		● >40A		● >40A	
	Fuse & fuse holder	○	○ ≤40A		○ ≤40A		○ ≤40A	
	REVO PC (3)	○	○					
CURRENT	CURRENT	SIZE	SIZE		SIZE		SIZE	
		480 to 600V	480 to 600V	690V	480 to 600V	690V	480 to 600V	690V
	30	SR0.SR1 (2)	SR3.SR6		SR4.SR7		SR5.SR8	
	35		SR3.SR6		SR4.SR7		SR5.SR8	
	40		SR3.SR6		SR4.SR7		SR5.SR8	
	60		SR12	S11	SR15	S11	SR16	S11
	75				SR15		SR16	
	90		SR15	S11	SR15	S11	SR16	S11
	120		SR15	S11	SR16	S13	SR17	S13
	150		SR15	S11	SR16	S13	SR17	S13
	180		SR15	S11	SR16	S13	SR17	S13
	210		SR15	S11	SR16	S13	SR17	S13
	300		S12		S14	S14	S14	S14
	350						S14	S14
	400		S12	S12	S14	S14	S14	S14
	450				S14	S14	S14	S14
	500		S12	S12	S14	S14	S14	S14
	600		S12	S12	S14	S14		
	700		S12	S12	S14	S14		
800		S15	S15	S16	S16	S17	S17	

● Standard ○ Option ■ CE standard + cUL® as an option ■ CE Only ■ cUL® Only

(1) 4-8-16 Cycles Simplified Burst Firing available with Analog Input only (2) See page 9 for current sizing

(3) REVO PC is an external unit designed to handle multiple zones, able to minimize energy cost, keep power factor close to 1 and add Field Bus. See REVO PC catalog.

REVO S & SSR SIZE AND DIMENSIONS



SR0 H 97 x W 36 x D 32 - 0,12 kg



SR1 H 97 x W 36 x D 92 - 0,29 kg



SR2 H 121 x W 36 x D 87 - 0,27 kg



SR3 H 121 x W 36 x D 125 - 0,44 kg



SR4 H 121 x W 72 x D 125 - 0,88 kg



SR5 H 121 x W 108 x D 125 - 1,32 kg



SR6 H 121 x W 36 x D 185 - 0,61 kg



SR7 H 121 x W 72 x D 185 - 1,22 kg



SR8 H 121 x W 108 x D 185 - 1,83 kg



SR12 H 269 x W 93 x D 170 - 3,4 kg
SR15 H 273 x W 93 x D 170 - 3,6 kg



SR13 H 269 x W 186 x D 170 - 6,8 kg
SR16 H 273 x W 186 x D 170 - 7,0 kg



SR14 H 269 x W 279 x D 170 - 10,2 kg
SR17 H 273 x W 279 x D 170 - 10,6 kg



S11 H 440 x W 137x D 270 - 10,5 kg



S12 H 520 x W 137 x D 270 - 15 kg



S13/S14 H 440/520 x W 262 x D 270 - 18/22 kg



S15 H 560 x W 137x D 270 - 17,2 kg



S16 H 560 x W 275 x D 270 - 34,4 kg



S17 H 560 x W 411 x D 270 - 51,6 kg

REVO SSR



SIZE SRO



Technical Specification


- **Dimensions:** SRO, SR1, (see page 7)
- **Load type:** Normal resistance, infrared long and medium waveform
- **Inputs:** SSR
- **Firing mode:** Zero Crossing
- **Operating temperature:** See graph on right page
- **Comply with EMC - CE**
- **Operating current:** see the graph on the right page.
This unit needs an heatsink, see the graph on the right page to size it
Max terminals current allowed is 40A

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
ORDER CODE	S	S	R	-	-	-	-	-	-	-	-	-	-	-	-	-
CURRENT				4	5	6										
description				code		note										
62A				0	6	2										
74A				0	7	4										
90A				0	9	0										
MAX VOLTAGE					7											
description					code	note										
480V					4											
600V					6											
VOLTAGE SUPPLY AUX					8											
description					code	note										
No auxiliary voltage supply					0											
INPUT					9											
description					code	note										
SSR					S											
FIRING					10											
description					code	note										
Zero Crossing Z					Z											
Random (For connection with REVO PC)					R											
CONTROL MODE					11											
description					code	note										
Open Loop					0											
FUSES & OPTION												12				
description												code	note			
No Fuse												0				
FAN VOLTAGE												13				
description												code	note			
No fan												0				
APPROVALS												14				
description												code	note			
CE EMC For European Market												0				
MANUAL												15				
description												code	note			
None												0				
Italian												1				
English												2				
German												3				
French												4				
VERSION												16				
description												code	note			
Std version												1				

REVO SSR/ANALOG



SIZE SR1



Technical Specification

- **Dimensions:** SR1 (see page 7)
- **Load type:** Normal resistance, infrared long and medium waveform
- **Inputs:** 0:10V; 4-20mA - SSR
- **Firing mode:** Zero Crossing - Burst firing
- **Operating temperature:** See the graph on the right page
- **Comply with EMC - CE**
- **Operating current:** see the graph on the right page. This unit needs an heatsink, see the graph on the right page to size it. Max terminals and fuse current allowed is 40A.

Option

All options below are available with fuse + fuse holder only



- Current Transformer
- Current Transformer + HB (heater break)
- Current Transformer + HB (heater break) + flat wiring system

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
ORDER CODE (Note 3)	S	S	R	-	-	-	-	-	-	-	-	-	-	-	-	-
CURRENT				4	5	6										
description				code		note										
62A				0	6	2										
74A				0	7	4										
90A				0	9	0										
MAX VOLTAGE					7											
description					code	note										
480V					4											
600V					6											
VOLTAGE SUPPLY AUX					8											
description					code	note										
Without HB no auxiliary voltage supply					0											
24V ac-dc with HB and Analog					4											
INPUT					9											
description					code	note										
SSR					S											
0:10V Analog Input					V	2										
4:20 mA Analog Input					A	2										
FIRING					10											
description					code	note										
Zero Crossing					Z											
Random (For connection with REVO PC)					R											
Burst firing 4 Cycles on at 50% Power Demand					4											
Burst firing 8 Cycles on at 50% Power Demand					8											
Burst firing 16 Cycles on at 50% Power Demand					6											
CONTROL MODE												11				
description												code	note			
Open Loop												0				
FUSES & OPTION												12				
description												code	note			
Fuse + Fuse Holder												F				
Fuse + Fuse Holder + CT												Y				
Fuse + Fuse Holder + CT + HB												H	2			
Fuse + Fuse Holder + CT + HB + Flat Cable												X	2			
FAN VOLTAGE												13				
description												code	note			
No fan												0				
APPROVALS												14				
description												code	note			
CE EMC For European Market												0				
MANUAL												15				
description												code	note			
None												0				
Italian												1				
English												2				
German												3				
French												4				
VERSION												16				
description												code	note			
Std version												1				
High Sensitivity HB below 5A												5				



Note (1) see page 9 for current sizing. Note (2) Option available only with fuse + fuse holder.

Note (3) All the Revo Analog version have fuse + fuse holder. More details on "Revo SSR Analog" Manual



CURRENT SIZING FOR REVO SSR/SSR ANALOG



R062 MODULE Power Dissipation versus on state Current and ambient Temperature



R074 MODULE Power Dissipation versus on state Current and ambient Temperature



R090 MODULE Power Dissipation versus on state Current and ambient Temperature

REVO SX

230V



480V



Size SR2-230V H 121 x W 36 x D 87 - 0,27 kg


Size SR2-480V H 121 x W 48 x D 87 - 0,27 kg

Specification


- Available in three versions as shown below
- Each unit includes Fuse and Fuse Holder, thyristor and heat sink with its own Firing circuit
- Zero Crossing Firing
- Isolated input
- LED for On Off Status indication
- LED for fuse failure indication
- Plug in connection for auxiliary and power terminations
- Small dimensions Width: 36 Depth: 86 Height:121
- Din rail mounting or screw mounting
- Can be used in applications with many zones and low power as thermoforming, blow Moulding and Hot Runners

Diagram of control connection examples


4x3,5A - 230V



3x4,5A - 230V



2x7A - 230V



ORDER CODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
	R	S	X	-	-	-	-	-	-	-	-	-	-	-	-	-
NUMBER OF ZONES X CURRENT RATING				4	5	6										
description				code		note										
4 zones 3,5A each				4	0	3										
3 zones 4,5A each				3	0	4										
2 zones 7A each				2	0	7										
MAX VOLTAGE					7											
description					code	note										
230V					2											
480V					4											
VOLTAGE SUPPLY AUX					8											
description					code	note										
No Auxiliary Voltage with 230V					0											
24 Vdc with 480V					4											
INPUT					9											
description					code	note										
SSR					S											
FIRING					10											
description					code	note										
Zero Crossing					Z											
Random (used with REVO-PC)					R											
CONTROL MODE					11											
description					code	note										
Open Loop					0											
FUSES & OPTION												12				
description												code	note			
Fuse + Fuse Holder												F				
FAN VOLTAGE												13				
description												code	note			
No Fan Voltage												0				
APPROVALS												14				
description												code	note			
CE EMC For European Market												0				
MANUAL												15				
description												code	note			
None												0				
Italian												1				
English												2				
German												3				
French												4				
VERSION												16				
description												code	note			
Version 1												1				

REVO SX




Size SR25 H 180 x W 116 x D 183 - 2,35 kg

Specification

- Available in different type with two or three independent channels
- Currents: 50, 60, 75 and 90A
- 480V or 600V Max Voltage
- Each unit includes two or three Integrated Fuses & thyristors with its own firing circuit, they share a heat sink
- Zero Crossing Firing
- Isolated input
- Screw mounting
- Can be used in applications with many zones in combination with REVO PC series to get power synchronization, communication, measurement and diagnostic

Diagram of control connection examples



ORDER CODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16					
	R	S	X	-	-	-	-	-	-	-	-	-	-	-	-	-					
NUMBER OF ZONES X CURRENT RATING				4	5	6															
description				code		note															
2 zones 50A each				2	5	0															
2 zones 60A each				2	6	0															
2 zones 75A each				2	7	5															
2 zones 90A each				2	9	0															
3 zones 50A each				3	5	0															
3 zones 60A each				3	6	0															
3 zones 75A each				3	7	5															
3 zones 90A each				3	9	0															
MAX VOLTAGE							7														
description							code														
480V							4														
600V							6														
VOLTAGE SUPPLY AUX								8													
description								code													
No Auxiliary Voltage								0													
INPUT									9												
description									code												
SSR									S												
FIRING										10											
description										code											
Zero Crossing										Z											
CONTROL MODE																11					
description																code					
Open Loop																0					
FUSES & OPTION																	12				
description																	code				
Integrated fuses																	F				
FAN VOLTAGE																		13			
description																		code			
No Fan Voltage (only RSX250)																		0			
Standard: 24Vdc Fan (All unit with exception of RSX250)																		3			
APPROVALS																			14		
description																			code		
CE EMC For European Market																			0		
MANUAL																				15	
description																				code	
None																				0	
Italian																				1	
English																				2	
German																				3	
French																				4	
VERSION																					16
description																					code
Version 1																					1


REVO S 1PH



SIZE SR6



SIZE S15



Technical Specification

- **Dimensions:** See size and dimensions on page 7
- **Load type:** Normal resistance, infrared long and medium waveform
- **Inputs:** SSR Standard, 0:10V, 4:20mA and Heater Break alarm are options
- **Firing mode:** Zero Crossing, Burst Firing available with analogue input only
- **Operating temperature:** 0 to 40°C without derating
- **Comply with EMC,** cULus® 508 listed and cUL® listed up to 700A as an option
- **100 kA:** Short Circuit Current rating (SCCR) up to 600V, 700A (see Tab. page 6)
- **Data sheet:** More details on "Revo S 1PH" Manual

Option

- Analog input: 4/20 mA or 0/10V
- Heater Break Alarm + Current Transformer
- Current Transformer mounted inside

ORDER CODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
	R	S	1	-	-	-	-	-	-	-	-	-	-	-	-	-
CURRENT				4	5	6										
description				code		note										
30A				0	3	0										
35A				0	3	5										
40A				0	4	0										
60A				0	6	0										
90A				0	9	0										
120A				1	2	0										
150A				1	5	0										
180A				1	8	0										
210A				2	1	0										
300A				3	0	0										8
400A				4	0	0										
500A				5	0	0										
600A				6	0	0										
700A				7	0	0										
800A				8	0	0										5
MAX VOLTAGE							7									
description							code									
480V							4									
600V							6									
690V							7									4,5
AUX VOLTAGE SUPPLY								8								
description								code								
≤ 210A								0								9
No Aux Voltage needed if HB option and/or Analog Input option NOT selected								4								9
Aux Volt 24V ac-dc needed with HB option and/or Analog Input option selected																
> 210A																
Main Supply Voltage																
Aux Voltage Range																
100/120Vac								90 to 135V Vac								1
200/208/230/240Vac								180 to 265V Vac								2
277Vac								238 to 330V Vac								3
380/415/480Vac								342 to 528V Vac								5
600Vac								540 to 759V Vac								6
690Vac								540 to 759V Vac								7
INPUT																
description																
SSR								S								
0:10V dc								V								
4:20mA								A								
FIRING																
description																
Zero Crossing																10
Burst Firing 4 Cycles On at 50% Power Demand																4
Burst Firing 8 Cycles On at 50% Power Demand																8
Burst Firing 16 Cycles On at 50% Power Demand																6
Random Firing (used with REVO-PC)																R
CONTROL MODE																
description																
Open Loop																0
FUSES & OPTION																
description																
≤ 40A																
No Fuse for all Units ≤ 40A																F
Fuse + Fuse Holder																Y
Fuse + Fuse Holder + CT																H
Fuse + Fuse Holder + CT + HB																X
Fuse + Fuse Holder + CT + HB with Flat Cable Connection																5,6
> 40A																
Fixed Fuses Std for all Units > 40A																F
Fixed Fuses Std + CT + HB																H
FAN VOLTAGE																
description																
No Fan < 90A																0
Fan 115Vac ≥ 90A																1
Fan 230Vac ≥ 90A Std Version																2
Fan 24Vdc ≥ 90A																3
APPROVALS																
description																
CE EMC For European Market																0
CE EMC + cUL® listed and cULus 508® listed																L
MANUAL																
description																
None																0
Italian																1
English																2
German																3
French																4
VERSION																
description																
Std unit with one fuse																1
High Sensitivity HB below 5A																5

- Note (1)** Fixed Fuses over 40A
Note (2) Available only with Analog input
Note (3) Load voltage must be included in Selected Auxiliary Voltage Range for units >210A
Note (4) Available on unit ≥60A
Note (5) This unit is available with CE only
Note (6) Needs TU-RS2 Terminal units
Note (7) See Revo PC catalog
Note (8): 690V not available
Note (9) This option is not available with Max Voltage equal to 690V. In this case please use the other Auxiliary Voltage Supplies


REVO S 2PH



SIZE SR7



SIZE S14



Technical Specification

- **Dimensions:** See size and dimensions on page 7
- **Load type:** Normal resistance, infrared long and medium waveform
- **Inputs:** SSR Standard, 0:10V, 4:20mA and Heater Break alarm are options
- **Firing mode:** Zero Crossing, Burst Firing available with analogue input only
- **Operating temperature:** 0 to 40°C without derating
- **Comply with EMC,** cUL us® 508 listed and cUL® listed up to 700A as an option
- **100 kA:** Short Circuit Current rating (SCCR) up to 600V, 700A
- **Data sheet:** More details on "Revo S 2PH" Manual

Option

- Analog input: 4/20 mA or 0/10V
- Current Transformer mounted inside
- Current Transformer + HB Alarm

ORDER CODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
	R	S	2	-	-	-	-	-	-	-	-	-	-	-	-	-
CURRENT			4	5	6											
description				code	note											
30A				0 3 0												
35A				0 3 5												
40A				0 4 0												
60A				0 6 0												
75A				0 7 5	7											
90A				0 9 0	5											
120A				1 2 0												
150A				1 5 0												
180A				1 8 0												
210A				2 1 0												
300A				3 0 0												
400A				4 0 0												
450A				4 5 0												
500A				5 0 0												
600A				6 0 0												
700A				7 0 0												
800A				8 0 0	5											
MAX VOLTAGE				7												
description				code	note											
480V				4												
600V				6												
690V				7	4, 5											
AUX VOLTAGE SUPPLY				8												
≤ 210A				code	note											
No Aux Voltage needed if HB option and/or Analog Input option NOT selected				0	9											
Aux Volt 24V ac-dc needed with HB option and/or Analog Input option selected				4	9											
> 210A																
Main Supply Voltage				Aux Voltage Range												
100/120Vac				90 to 135V Vac	1	3										
200/208/230/240Vac				180 to 265V Vac	2	3										
277Vac				238 to 330V Vac	3	3										
380/415/480Vac				342 to 528V Vac	5	3										
600Vac				540 to 759V Vac	6	3										
690Vac				540 to 759V Vac	7	3										
INPUT				9												
description				code	note											
SSR				S												
0:10V dc				V												
4:20mA				A												
FIRING										10						
description										code	note					
Zero Crossing										Z						
Burst Firing 4 Cycles On at 50% Power Demand										4	2					
Burst Firing 8 Cycles On at 50% Power Demand										8	2					
Burst Firing 16 Cycles On at 50% Power Demand										6	2					
CONTROL MODE										11						
description										code	note					
Open Loop										0						
FUSES & OPTION										12						
≤ 40A										code	note					
No Fuse for all Units ≤ 40A										0						
Fuse + Fuse Holder ≤ 40A										F						
Fuse + Fuse Holder + CT ≤ 40A										Y						
Fuse + Fuse Holder + CT + HB with Terminals										H						
Fuse + Fuse Holder + CT + HB with Flat Cable Connection										X	5, 6					
> 40A																
Fixed Fuses Std for all Units > 40A										F	1					
Fixed Fuses Std + CT + HB										H						
FAN VOLTAGE										13						
description										code	note					
No Fan < 60A										0						
Fan 115V ≥ 60A										1						
Fan 230V ≥ 60A Std Version										2						
Fan 24Vdc ≥ 60A										3						
APPROVALS										14						
description										code	note					
CE EMC For European Market										0						
CE EMC + cUL® listed and cULus 508® listed										L	7					
MANUAL										15						
description										code	note					
None										0						
Italian										1						
English										2						
German										3						
French										4						
VERSION										16						
description										code	note					
Std version										1						
High Sensitivity HB below 5A										5						

Note (1) Fixed Fuses over 40A

Note (3) Load voltage must be included in Selected Auxiliary Voltage Range for unit > 210A

Note (4) Available on unit ≥60A

Note (2) Available with Analog input only

Note (5) This unit is available with CE only

Note (6) Needs TU-RS2 Terminal units

Note (9) This option is not available with Max Voltage equal to 690V. In this case please use the other Auxiliary Voltage Supplies

Note (7) 75A unit is available with cUL only


REVO S 3PH



SIZE SR8



SIZE S13



Technical Specification

- **Dimensions:** See size and dimensions on page 7
- **Load type:** Normal resistance, infrared long and medium waveform
- **Inputs:** SSR Standard, 0:10V, 4:20mA and Heater Break alarm are options
- **Firing mode:** Zero Crossing, Burst Firing available with analogue input only
- **Operating temperature:** 0 to 40°C without derating
- **Comply with EMC,** cUL us® 508 listed and cUL® listed up to 500A as an option
- **100 kA:** Short Circuit Current rating (SCCR) up to 600V, 500A
- **Data sheet:** More details on "Revo S 3PH" Manual

Option

- Analog input: 4/20 mA or 0/10V
- Current Transformer mounted inside
- Current Transformer + HB Alarm

ORDER CODE	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
	R	S	3	-	-	-	-	-	-	-	-	-	-	-	-	-
CURRENT				4	5	6										
description				code		note										
30A				0	3	0										
35A				0	3	5										
40A				0	4	0										
60A				0	6	0										
75A				0	7	5	7									
90A				0	9	0	5									
120A				1	2	0										
150A				1	5	0										
180A				1	8	0										
210A				2	1	0										
300A				3	0	0										
350A				3	5	0										
400A				4	0	0										
450A				4	5	0										
500A				5	0	0										
800A				8	0	0	5									
MAX VOLTAGE					7											
description					code	note										
480V					4											
600V					6											
690V					7	4, 5										
AUX VOLTAGE SUPPLY					8											
description					code	note										
≤ 210A																
No Aux Voltage needed if HB option and/or Analog Input option NOT selected					0	9										
Aux Volt 24V ac-dc needed with HB option and/or Analog Input option selected					4	9										
> 210A																
Main Supply Voltage																
Aux Voltage Range																
100/120Vac					90 to 135V Vac	1	3									
200/208/230/240Vac					180 to 265V Vac	2	3									
277Vac					238 to 330V Vac	3	3									
380/415/480Vac					342 to 528V Vac	5	3									
600Vac					540 to 759V Vac	6	3									
690Vac					540 to 759V Vac	7	3									
INPUT					9											
description					code	note										
SSR					S											
0:10V dc					V											
4:20mA					A											
FIRING										10						
description										code	note					
Zero Crossing										Z						
Burst Firing 4 Cycles On at 50% Power Demand										4	2					
Burst Firing 8 Cycles On at 50% Power Demand										8	2					
Burst Firing 16 Cycles On at 50% Power Demand										6	2					
CONTROL MODE											11					
description											code	note				
Open Loop											0					
FUSES & OPTION												12				
description												code	note			
≤ 40A																
No Fuse for all Units ≤ 40A												0				
Fuse + Fuse Holder ≤ 40A												F				
Fuse + Fuse Holder + CT ≤ 40A												Y				
Fuse + Fuse Holder + CT + HB with Terminals												H				
Fuse + Fuse Holder + CT + HB with Flat Cable Connection												X	5, 6			
> 40A																
Fixed Fuses Std for all Units > 40A												F	1			
Fixed Fuses Std + CT + HB												H				
FAN VOLTAGE													13			
description													code	note		
No Fan < 60A													0			
Fan 115Vac ≥ 60A													1			
Fan 230Vac ≥ 60A Std Version													2			
Fan 24Vdc ≥ 60A													3			
APPROVALS														14		
description														code	note	
CE EMC For European Market														0		
CE EMC + cUL® listed and cULus 508® listed														L	7	
MANUAL															15	
description															code	note
None															0	
Italian															1	
English															2	
German															3	
French															4	
VERSION																16
description																code
Std Version																1
High Sensitivity HB below 5A																5

Note (1) Fixed Fuses over 40A

Note (2) Available with Analog input only

Note (3) Load Voltage must be included in selected Auxiliary Voltage Range for unit > 210A

Note (6) Needs TU-RS2 Terminal units

Note (7) 75A unit is available with cUL only

Note (4) Available on unit ≥60A

Note (5) This unit is available with CE only

Note (9) This option is not available with Max Voltage equal to 690V. In this case please use the other Auxiliary Voltage Supplies

REVO IS A SYSTEM NOT JUST A PRODUCT

REVO'S INNOVATIVE DESIGN AIDS SYSTEM INTEGRATION WITH THE FOLLOWING AUXILIARY UNITS:

COPPER BAR

REVO can be mounted on copper bars as shown in the image with Length 12:30 mm and thickness 5:10 mm
Lateral Support for 3 copper bars **Code:** SC3-30
Lateral Support for 4 copper bars **Code:** SC4-30



BASE PLATE

Different type of base plate are available
The Base Plate have 3 Off Screw terminals 16 mm
W 54 x L 200 **Code:** BP-54-200
W 72 x L 200 **Code:** BP-72-200
W 54 x L 260 **Code:** BP-54-260



CABINET

The image shows a cabinet under construction with copper bars mounted on the back panel. This system is designed for optimal high short circuit current and the 100KA SCCR of the REVO S family.
Using copper bars in this way, it is not necessary to wire power cables from automatic circuit breakers to each thyristor unit but just to the power terminals of each bus bar. The plug-in base plates and therefore the complete zone, can easily be replaced should a fault occur.



CABINET

The image shows a finished cabinet with 60 temperature control zones. Mounting with the copper bus bar system results in a clean and professional cabinet.





Italy

CD Automation Srl
Via Picasso, 34/36
20025 Legnano MI
Italy
T +39 0331 577479
F +39 0331 579479
sales@cdautomation.com
www.cdautomation.com

United Kingdom

CD Automation UK Ltd
Unit 9 Harvington Business Park
Brampton Road, Eastbourne
East Sussex, BN22 9BN
England
T +44 1323 811100
info@cdautomation.co.uk
www.cdautomation.co.uk

India

M/s Toshcon CD Automation Pvt. Ltd.
H1 - 75 Gegal Industrial Area
Ajmer - 305023 (Raj.)
India
T +91 145 2791112
T +91 145 6450601/2/3
sales.cd@toshcon.com
www.cdautomation.in