

REVEX 1PH

ORDER CODE:

	1	2	3	4	5	6		7	8	9	10	11	12	13	14	15	16
REVEX 1PH	R	X	1	-	-	-	-	-	-	-	-	-	-	-	-	-	-

CURRENT		FUSES		
description	description	4	5	6
30A	External Fuse	0	3	0
35A	External Fuse	0	3	5
40A	External Fuse	0	4	0
60A	Fixed Fuses Included	0	6	0
90A	Fixed Fuses Included	0	9	0
120A	Fixed Fuses Included	1	2	0
150A	Fixed Fuses Included	1	5	0
180A	Fixed Fuses Included	1	8	0
210A	Fixed Fuses Included	2	1	0
280A	Fixed Fuses Included	2	8	0

MAX VOLTAGE	
description	code
480V	4
600V	6

MAIN SUPPLY VOLTAGE	
description	code
24Vdc	4

MAIN INPUT	
description	code
SSR	S
0:20mA	B
4:20mA	A
0:10V	V
10KPot	K

FIRING		START OPTION	
description	description	code	
Single Cycle	No Soft Start	C	
	Linear Soft Starter	S	
Half Cycle	No Soft Start	H	
	Linear Soft Starter	L	
	Soft Start for short wave Infrared Lamp	I	
Burst Firing	No Soft Start	B	
	Linear Soft Starter	J	
Phase Angle	No Soft Start	P	
	Linear Soft Starter	E	
Delayed Triggering	No Soft Start	D	
	Linear Soft Starter	T	
Zero Crossing	No Soft Start	Z	
	Linear Soft Starter	R	

CONTROL MODE	
description	code
Open Loop	0
Voltage	U
Voltage Square	Q
Current	I
Current Square	A
Power VxI	W

OPTION	
description	code
Option code - see following table	-

FAN VOLTAGE	
description	code
No Fan < 90A	0
Fan 24Vdc ≥ 90A	3

APPROVALS	
description	code
CE EMC For European Market	0

LOAD TYPE	
description	code
1 PH Normal Resistance	0
1 PH IRSW Infrared Short Wave	1
1 PH MoSi2 Heaters	2
1 PH SiC Heaters	3
1 PH Transformer Coupled with Normal Resistance	4
1 PH Transformer Coupled with MoSi2 Heaters	5
1 PH Transformer Coupled with SiC Resistance	6
1 PH Transformer Coupled with UV Lamp	7

VERSION	
description	code
Standard version - N*1 Modbus® RTU std.	0

Option Code Table (digit 12)

REVEX 1PH from 30 to 40A			
Current Limit	Heater Break	Display	Option Code (digit 12)
Y	Y	N	2
Y	N	N	3
N	N	N	4
Y	Y	Y	5
Y	N	Y	6
N	N	Y	7
N	Y	Y	9
N	Y	N	D

REVEX 1PH from 60 to 280A				
Current Limit	Heater Break	Fuse	Display	Option Code (digit 12)
Y	Y	Y	Y	0
Y	Y	Y	N	1
Y	Y	N	N	2
Y	N	N	N	3
N	N	N	N	4
Y	Y	N	Y	5
Y	N	N	Y	6
N	N	N	Y	7
N	Y	Y	N	8
N	Y	N	Y	9
N	N	Y	Y	A
N	N	Y	N	B
N	Y	Y	Y	C
N	Y	N	N	D
Y	N	Y	N	E
Y	N	Y	Y	F

N option you want removed
Y It serves my project