

# CD3000S 3PH 15-90A

## ORDER CODE:

	<b>1</b>	<b>2</b>	<b>3</b>	<b>4</b>	<b>5</b>	<b>6</b>		<b>7</b>	<b>8</b>	<b>9</b>	<b>10</b>	<b>11</b>	<b>12</b>	<b>13</b>	<b>14</b>	<b>15</b>	<b>16</b>
<b>CD3000S 2PH</b>	<b>D</b>	<b>S</b>	<b>3</b>	-	-	-	-	-	-	-	-	-	-	-	-	-	-

CURRENT (A)					
description	Code	OLD code	Note		
15A	0 1 5	15A			
30A	0 3 0	30A			
45A	0 4 5	45A			
60A	0 6 0	60A			
75A	0 7 5	75A			
90A	0 9 0	90A			

OPERATING VOLTAGE (V)					
description	Code	OLD code	Note		
From 24V to Max Load Voltage	not in the code	--_V			

MAX LOAD VOLTAGE (V)					
description	Code	OLD code	Note		
480V	4				
600V	6				

AUXILIARY VOLTAGE (V)					
description	Code	OLD code	Note		
NO Auxiliary Voltage supply	0	NO /			

INPUT					
description	Code	OLD code	Note		
SSR	S	SSR /			

FIRING					
description	Code	OLD code	Note		
Zero Crossing	Z	ZC /			

CONTROL MODE					
description	Code	OLD code	Note		
Open loop	0	not in the code			

FUSES & OPTION					
description	Code	OLD code	Note		
No Fuse	0	NF / -			
External Fuse & Fuse Holder	F	EF / -			

FAN VOLTAGE					
description	Code	OLD code	Note		
No Fan for unit <45A	0	- /			
Fan 110V Option - for 45A to 90A units	1	110VFAN /			
Fan 220V Standard - for 45A to 90A units	2	not in the code			

APPROVALS					
description	Code	OLD code	Note		
CE EMC for European Market	0	- /			
CE EMC + cUL us listed	L	UL /			

MANUAL					
description	Code	OLD code	Note		
None	0	NM			
Italian	1	IM			
English	2	EM			
German	3	GM			
French	4	FM			

IP PROTECTION					
description	Code	OLD code	Note		
Standard IP20 (all unit excluded 45A to 90A)	0	- /			
External IP20 protection for size S8 (45A to 90A)	P	EP /			<b>1</b>

**(1)** IP20 is standard on all units with exception of S8 size (45-90A).  
To complain IP20 use "P" option at digit 16

## Old Code (example):

Model	Current (A)	Operating Voltage (V)	Ma x Load Voltage (V)	Aux Voltage (V)	Input	Firing	Fuses	HB Option	EP Option	Approvals	Manual
CD3000S 3PH /	90A /	400V /	480V /	NO /	SSR /	ZC /	EF /	- /	EP /	UL /	EM

## New Code ERP Friendly (example):

	<b>1</b>	<b>2</b>	<b>3</b>	<b>4</b>	<b>5</b>	<b>6</b>		<b>7</b>	<b>8</b>	<b>9</b>	<b>10</b>	<b>11</b>	<b>12</b>	<b>13</b>	<b>14</b>	<b>15</b>	<b>16</b>
<b>CD3000S 3PH</b>	<b>D</b>	<b>S</b>	<b>3</b>	<b>0</b>	<b>9</b>	<b>0</b>	-	<b>4</b>	<b>0</b>	<b>S</b>	<b>Z</b>	<b>0</b>	<b>F</b>	<b>2</b>	<b>L</b>	<b>2</b>	<b>P</b>